






-  • Überladeschutz
-  • Overcharge protection




ALCT 6-24/10 Art.-Nr. | Part No. 1001-0014

-  • Verschiedene Ladeströme wählbar: 1A bei 6V, 12V, 24V
5A bei 12V, 24V
10A bei 12V



COLD TEMP Modus: Wird empfohlen bei Temperaturen unter 5°C, dadurch wird die Batterie auch bei kalten Temperaturen zu 100% vollgeladen.

REFRESH Modus: Das Ladegerät erkennt automatisch, wenn die Batterie tiefentladen ist, und lädt diese schonend durch pulsierende Ladeströme für 20Min. bis eine Grundspannung erreicht ist. Danach kann ein normaler Ladevorgang vorgenommen werden.

-  • Adjustable charging current: 1A - 6V, 12V, 24V
5A - 12V, 24V
10A - 12V

COLD TEMP mode: At temperatures below 5 °C (41 °F) we recommend the "COLD TEMPERATURE" mode, through this, the battery will be fully charged to 100% despite the cold.

REFRESH mode: If the battery is completely discharged, the charger automatically switches to refresh mode and charges the battery for 20min. by pulse charging until a sufficient voltage for the normal charging process has been reached. After the completion of the refresh mode a normal charging process can be started.

-  • Automatische Spannungserkennung
-  • Automatic voltage identification/Autosensing



BLEILADEGERÄT - ALCT 6-24/10

LEAD ACID CHARGER - ALCT 6-24/10

NEU 2013
NEW 2013

ALCT 6-24/10

- > Ladegerät für 6V, 12V- und 24V Bleiakkus (Blei-Gel, Blei-Vlies, Blei-Säure)
- > Mit Hilfe der hochwertigen Polklemmen ist eine schnelle und zuverlässige Kontaktierung der Bleiakkus möglich.
- > Automatische Spannungserkennung
- > Übersichtliches LED-Display - einfach zu bedienen
- > Ladestrom einstellbar
- > Automatischer REFRESH Modus, wenn die Batterie tiefentladen ist
- > Wählbarer COLD TEMP Modus bei kalten Temperaturen
- > Batterie-Defekt-Erkennung
- > 3-stufige Batteriestatusanzeige (35% - 70% - 100%)
- > Elektronischer Schutz gegen Kurzschluss, Verpolung und Überladung
- > Automatische Nachladung, wenn die Batterie am Gerät angeschlossen bleibt
- > Ideal zur Überwinterung von Bleiakkus - Tiefentladung ausgeschlossen
- > Automatische Starthilfeunterstützung (6V-1A | 12V-10A | 24V-5A)
- > Netz- und Ladekabel jeweils 180cm lang
- > Praktisches Kabelaufbewahrungsfach integriert, dadurch sind alle Kabel immer sicher verstaut

TECHNISCHE DATEN

- > Batteriekapazität 4,5Ah - 240Ah
- > Gewicht: nur 1.300g durch moderne Schaltnetzteiltechnik
- > Betriebsspannung: 230V / 50Hz
- > Abmessung (BxHxT): 272x194x142 mm

ALCT 6-24/10

- > Lead acid charger for 6V/12V/24V lead acid, SLA batteries
- > With the help of high-quality pole terminals a fast and reliable contact of lead acid batteries is possible
- > Automatic voltage identification / Autosensing
- > Clear LED display - easy to use
- > Adjustable charging current
- > Automatic REFRESH mode, if the battery is completely discharged
- > Selectable COLD TEMP mode at cold temperatures
- > Faulty cell detection
- > 3-step charging status indicator (35% - 70% - 100%)
- > Protection against short-circuit, wrong polarity and overcharge
- > Automatic start of recharge, if the battery is left connected to the charger
- > Ideal maintenance of lead acid batteries during winter time - no deep discharge
- > Automatic start function (6V-1A | 12V-10A | 24V-5A)
- > Power and charging cable each 180cm
- > Practical cable storage integrated, the cables are always stored safely

TECHNICAL DETAILS

- > Battery capacity: 4,5Ah - 240Ah
- > Weight: only 1.300g due to modern switching power supply technology
- > Operating voltage: 230V / 50Hz
- > Dimensions (WxHxD): 272x194x142mm

INFOS:

Produktname | Product name:
ALCT 6-24/10

Art.-Nr. | Part No.:
1001-0014

EAN-Code:
4013674021512

VE | PU:
4 (400x295x290mm)

Lieferbar | Available:
KW 28 | Week 28

**Zolltarifnummer |
Customs tariff number:**
85044055

UVP | MSRP:
99,90 €

Materialgruppe | Material group:
01

Notizen | Notes:

Warranty
Guarantee **3** Years
Jahre



Hochwertige Polklemmen | High-quality pole terminals



Praktisches Kabelaufbewahrungsfach | Practical cable storage